

LP-LED4X

4 HEAD LED LIGHTING SYSTEM



Overview

Low profile design with convenient bar handles make the LP-LED4X easy to transport. Innovative through-hole stand mount design allows multiple units to be used on a standard speaker stand for large scale mobile applications. Contractors and touring companies will appreciate the integrated flypoints that ensure safe installation or truss mounting in touring rigs, club installs or theatre applications.

Our iOS App controls up to four individual LP-LED4X fixtures via Bluetooth, and Android.

Features

- Four Pods each with Four RGBW LEDs
- Bluetooth Compatible
- Operates in Standalone Mode, Controlled Via Yorkville Proprietary Communication Protocol, Integrated DMX I/O, Bluetooth Control (IOS) and Android
- Integrated Microphone for Sound Active mode
- 31 Pre-set Colors per Pod in Standalone Mode
- Master Brightness Control
- Audio Chase Input (Line Level or Speaker Level)
- Pole Adapter goes right through unit allowing stacking of multiple LP-LED's or to be mounted under a loudspeaker
- Made in Canada

Specifications

System Type	LED Lighting System
Powered or Passive	Powered
Power Consumption LEDs	14 watts per LED (4 LEDs, 56 watts per pod)
Power Consumption	200VA, 1.7A @ 120VAC Nominal
Stand Mount Size	1 3/8-inch Round Pole Through Design
Manual Controls	Master Brightness Lamp Colours
Effect Modes	Colour Chase / Colour Fade / Audio Chase / Bluetooth
Bluetooth Control App	IOS & Android
DMX	Shielded 3-pin XLR Cable
Sound Active Mode	Integrated Microphone
Audio Input	Line Level or Speaker Level
Yorkville Controller	LP-C12 or LP-C4
Dimensions (LWH inches)	31 x 4.8 x 8
Dimensions (LWH cm)	78.8 x 12.25 x 20.4
Weight	14.6 lbs (6.6 kg)
Box Dimensions (LxWxH, inches)	34 x 10 x 10
Box Dimensions (LxWxH, cm)	86 x 25 x 25

Specifications subject to change without notice



Bluetooth™
Available for
FREE DOWNLOAD

The iOS and Android App, via Bluetooth, controls up to 4 individual LP-LED4X and LP-LED2X fixtures.

GET IT ON
Google Play

Download on the
App Store

Type: yorkville LP-control

