

# PX1700

2 x 850 Watt Power Amplifier



## Overview

Perfect for clubs or concert halls, the Yorkville PX Series PX1700 power amplifier delivers up to 1700 watts (2 x 850 watts @ 2 ohms). XLR and 1/4-inch inputs, binding post and Speakon™ outputs ensure the PX1700 can be integrated into virtually any high performance sound system or mobile PA.

## Features

- Easily Drives Reactive Loads
- Delivers 1700 Watts Bridged Mono @ 4 ohms
- 850 Watts per Channel @ 2 ohms
- Recessed Front Panel Gain Controls
- Advanced Protection Schemes
- Front Panel Power, Protect, Activity and Clip LED's
- Speakon™ and Binding Post Outputs
- Balanced XLR & 1/4-inch TRS Inputs
- Sturdy All-Steel Construction



## Specifications

Amplifier class	Class-H
Continuous Average Power BCD (Watts)	400 @ 8 Ohms 600 @ 4 Ohms 850 @ 2 Ohms
Continuous Average Power Bridged BCD (Watts)	1700
Burst Average Power BCD (Watts)	600 @ 8 Ohms 1000 @ 4 Ohms 850 @ 2 Ohms
Burst Average Power Bridged BCD (Watts)	1700
Frequency Response (Hz, +/- 1dB)	30Hz to 20kHz
Max Voltage Gain (dB)	31dB
Stereo / Mono / Bridge (S/M/B)	Yes
Protection	DC/Load/Thermal
Limiter	Defeatable
Cooling	Fan
Inputs - XLR	Yes (x2)
Inputs - 1/4" Jacks	Yes (x2)
Outputs - Speakon 4-pin	Yes
Outputs - Binding Post	Yes
Power Consumption (typ/max)	700/1500
Rack Spaces	Two
Transformer Type	Toroidal
Dimensions (DWH / D fm ears, inches)	16 x 19 x 3.5
Dimensions (DWH / D fm ears, cm)	40.6 x 48.3 x 8.9
Weight (lbs / kg)	35/16
Box Dimensions (LxWxH, inches)	23 x 21 x 6.3
Box Dimensions (LxWxH, cm)	58 x 53 x 16

Specifications subject to change without notice